

以基因法則設計用於室內傳輸錯誤率最小之天線場型

Novel antenna pattern by the genetic algorithm to minimize bit error rate in indoor wireless communication

計劃編號：NSC 89-2213-E-032-037

執行期間：89年8月1日至90年7月31日

計劃主持人：丘建青

淡江大學電機系教授

一、中文摘要（關鍵字：遺傳演算法則、圓弧陣列天線，位元錯誤率）

在室內環境，由於多路徑效應造成的符際互擾問題，使得通訊位元錯誤率及失效率增加，是造成通話品質變差的主要原因。本計畫的目標是希望透過天線場型的調整，能夠降低信號接收的位元錯誤率。這樣的問題可以看成一種最佳化的問題，由於基因法則的好處在於不須列出變數和因變數的明顯數學關係亦能找出最佳解，因此使用基因法則作為最佳化的工具。和一般以天線場型為目標函數所不同的地方是，本計畫擬以降低室內通信傳輸位元錯誤率為目標函數，再利用基因法則作最佳化的調整，尋找出滿足最低傳輸位元錯誤率時的天線場型，此種場型最能滿足通訊的需求。

英文摘要（keyword: genetic algorithm, circular arc array antenna, bit error rate）

The genetic algorithm is used to synthesize the radiation pattern of the directional circular arc array to minimize the bit error rate (BER) performance in indoor wireless communication system. By using the impulse response of multipath channel, the performance of the synthesized antenna pattern on BPSK (binary phase shift keying) system with phase and timing recovery circuits can be calculated. Based on the topography of the antenna and the BER formula, the synthesis problem can be reformulated into an optimization problem and solved by the genetic algorithm. Numerical

results show that the synthesized antenna pattern is effective to combat the multipath fading and can increase the transmission rate of indoor millimeter wave system.

二、計畫緣由與目的

Wireless local loop networks have attracted considerable attention in recent years. However, the severe multipath fading, which are characteristics of the indoor radio channels, limit the data rate [1] - [3]. Applying appropriately narrow antenna beams can overcome this degradation [4], [5]. To synthesize the antenna pattern to minimize the BER performance, the excitation problems are reformulated as optimization problems. The genetic algorithm is a well-known algorithm, which uses random choice to search through a coding of a parameter space and find the global extreme of the problem. Most papers apply genetic algorithm for searching minimum sidelobe level of the antenna pattern [6]. However, this pattern cannot guarantee to obtain minimum BER performance of the communication system.

三、研究方法及成果

(A) Calculation of the channel characteristics

The equation used to model the multipath radio channel is a linear filter with an equivalent

baseband impulse response given by

$$h_b(t) = \sum_{k=0}^N s_k e^{j\phi_k} u(t - t_k) \dots\dots\dots(1)$$

where k is the path index, s_k is the path gain, ϕ_k is the phase shift and t_k is the time delay of the k th path. $u(\cdot)$ is the Dirac delta function.

The impulse response function for a given antenna pattern at any transmitter-receiver location is computed by modified shooting and bouncing ray/image (SBR/Image) techniques [7]. The SBR/Image method can deal with high frequency radio wave propagation in complex indoor environments.

(B) System block diagram

A BPSK (binary phase shift keying) system with raised cosine pulse shaping (rolloff factor ρ), phase and timing recovery circuits is considered. The equivalent baseband channel models are plotted in Fig. 2. The probability of error for this BPSK system is given by [8]

$$P_e = \sum_n p(a_n) \cdot \frac{1}{2} \text{erfc} \left[\frac{\sum_n a_n \text{Re}\{[h_s(t_s - nT) \otimes h_r(t_r - nT)] \cdot e^{-j\theta}\}}{t_n} \right] \dots\dots\dots(2)$$

where t_n is the standard deviation of the additive noise and $\text{erfc}(x) = \frac{2}{\sqrt{\pi}} \int_x^\infty e^{-y^2} dy$. Note that the error probability P_e in equation (2) which is related to $h_b(t)$ will be affected by the antenna pattern used.

(C) Pattern Synthesis of Arc Array by the Genetic Algorithm

Circular arrays have a number of well-known advantages over linear arrays, because of their symmetry. This property also carries over to arc arrays in which a small segment of the circular array is used to form the beam, and steering of the beam is now achieved

by appropriately selecting a segment or arc and weighting the element signals independently of the chosen segment. They are capable of giving nearly as good performance as circular arrays (of the same radius), and thus yielding considerable saving in hardware/signal processing.

The pattern synthesis procedure using the genetic algorithm to find the minimum BER performance begins with an array of fixed geometry with a set of starting excitations. The excitations are then changed until the minimum error probability is achieved. We assume an array of M directional elements with equal space situated over an circle of radius R as shown in Fig. 3. The angular spacing between consecutive elements is $2\pi/M$. An arc region of L element is “turned on” and is used to synthesize the desired pattern, which will minimize the error probability.

The genetic algorithm is a search algorithm based on the mechanics of natural selection and natural genetics. They find the global maximum of an objective function (or fitness function) of the problem by random search. In this case, both parameters are I_n and ρ_n . Then three operators - reproduction, crossover and mutation - are employed to search the optimization of the problem through a coding of a parameter space. The flow chart for the genetic algorithm is shown in Fig. 4.

In the synthesis procedure, the genetic algorithm is used to maximize the following object function to find the optimal antenna pattern:

$$SF = \left(\sum_i P_{e,i} \right)^{-1} \dots\dots\dots(3)$$

Here $P_{e,i}$ is the error probability for i th point. Note that the relationship of the antenna pattern

and the error probability $P_{e,i}$ cannot be formulated by simple equation. In fact, the antenna pattern will affect the impulse response h_b in equation (1). As a result, it affects the error probability $P_{e,i}$ in equation (2). The strong point of the genetic algorithm is that it can find out the solution even if the performance index cannot be formulated by simple equation. In our simulation, as soon as the object function (SF) changes by less than 1% in two successive generations, the algorithm will be terminated and a solution is then obtained.

(D) Numerical Results

To synthesize the optimal antenna pattern, circular array located on xy plane with radius $R=2.392\lambda$ and $M=30$ was considered. The spacing of elements on the arc is $\lambda/2$. Here λ is the wavelength. Next, let us consider a typical room as shown in Fig 1. In this room, assume that the 25cm-thick walls, floor and ceiling are all concrete materials with a complex dielectric constant $\nu_r = 6.5 - 0.43j$ at 57.5GHz [1], [10]. The transmitting antenna is a half-wave dipole and vertically polarized. It is located at the center of the room with coordinates (5.5m, 6m, 3.5m). The height of the receiving antenna is 1.5 meters. The excitation currents are computed by using the genetic algorithm via Eq. (10). The length of coding is set to be 16 bits (i.e., $Q=16$ bits). In other words, the bit number of a chromosome is 480 ($2 \times 15 \times 16$). The search range for the amplitude is chose from 0 to 1. Besides, the search range for the phase is from 0 to 2π . Population size is chosen as 1000. The mutation probability is set to be 1%.

The impulse response of the room for any

antenna pattern was calculated at 57.5 GHz by SBR/Image method. The number of ray tubes shooting from the transmitter is 200,000. The maximum number of bounces setting beforehand is five, and the convergence is confirmed. Since the extra attenuation at 57.5 GHz due to atmospheric absorption and scattering is negligible over small distance, the atmospheric attenuation is not considered in the simulation [2].

With all these parameters, the synthesis pattern by the genetic algorithm is shown in Fig. 5. The final BERs for multiple points are less than 10^{-7} respectively. It is clear the multipath is reduced by the optimal antenna. Comparing with the BER for omnidirection antenna is 10^{-3} , it is seen the BER reduced a lot. Many similar realizations have been done and it is found that the multipath effect is reduced by the optimal antenna and method for is very useful for wireless communication system.

四、結論與討論

Synthesizing optimal antenna pattern to minimize the BER performance in indoor wireless local loop is presented. The impulse response of the millimeter wave channel is computed by SBR/Image. By using the impulse response of the multipath channel and the synthesized antenna pattern, the BER performance of BPSK communication system is investigated. Based on the BER formulation, the synthesis problem can be reformulated into an optimization problem. In our approach, the object is defined as the inversion of BER instead of sidelobe level of the antenna. Numerical results show that the BER can be reduced a lot compared to the omnidirectional antenna in indoor wireless millimeter wave channel.

五、參考文獻

- [1] T. Manabe, Y. Miura and T. Ihara, "Effects of antenna directivity and polarization on indoor multipath propagation characteristics at 60 GHz," *IEEE J. Select. Areas Commun.*, vol. 14, pp. 441-448, April 1996.
- [2] A. M. Hammoudeh and G. Allen, "Millimetric wavelengths radiowave propagation for line-of-sight indoor microcellular mobile communications," *IEEE Trans. Veh. Technol.*, vol. 44, pp. 449-460, Aug. 1995.
- [3] R. J. C. Bultitude, R. F. Hahn, and R. J. Davies, "Propagation considerations for the design of an indoor broad-band communications system at EHF," *IEEE Trans. Veh. Technol.*, vol. 47, pp. 235-245, Feb. 1998.
- [4] G. Yang, K. Pahlavan and T. J. Holt, "Sector antenna and DFE modems for high speed indoor radio communication, " *IEEE Trans. Veh. Technol.*, vol. 43, pp. 925-933, Nov. 1994 .
- [5] M. R. Williamson, G. E. Athansasiadon and A. R. Nix, "Investigating the effects of antenna directivity on wireless indoor communication at 60 GHz," *PIMRC '97, The 8th IEEE International Symposium* vol. 2, pp. 635-639, Sept. 1997.
- [6] F. J. Ares, A. Rodriguez, E. Villanueva, and S. R. Rengarajan, "Genetic algorithms in the design and optimization of antenna array patterns," *IEEE Trans. Antennas and Propagat.*, vol. 47, pp. 506-510, Mar. 1999.
- [7] S. H. Chen and S. K. Jeng, "An SBR/Image approach for radio wave propagation in indoor environments with metallic furniture," *IEEE Trans. Antennas and Propagat.*, vol. 45, pp. 98-106, Jan 1997.
- [8] K. Pahlavan, "Comparison between the performance of QPSK, SQPSK, QPR, and SQPR systems over microwave LOS channels," *IEEE Trans. Commun.*, vol. 33, pp. 291-296, Mar. 1985.
- [9] Y. C. Jiao., W. Y. Wei, L. W. Huang, and H. S. Wu, "A new low-side-lobe pattern synthesis technique for conformal arrays," *IEEE Trans. Antenna Propag.*, Vol. 41, pp. 824-831, June 1993.
- [10] K. Sato, T. Manabe, T. Ihara, H. Saito, S. Ito, T. Tanaka, K. Sugai, N. Ohmi, Y. Murakami, M. Shibayama, Y. Konishi and T. Kimura, "Measurements of reflection and transmission characteristics of interior structure of office building in the 60GHz band," *Proc. IEEE International Symposium on Personal, Indoor and Mobile Radio Communication*, vol. 1, pp. 14-18, Oct. 1996.

Fig. 1

Fig. 3

Fig. 2(a)

Fig. 4

Fig. 2(b)

Fig. 5